

Visual Dimmer Testing Report Card

DATE TESTED 01/25/2022



Product Model # S21363, S21364, S21365

8W ST19 90CRI 2700K, 3000K, 4000K

MANUFACTURER	MODEL	Dimmer Watts	NUMBER LAMPS TESTED	OVERALL RESULTS													Dimming %	Good	Better	Best	Notes: High trim required			
				VISUAL RANGE	H.E. DEAD TRAVEL	L.E. DEAD TRAVEL	STEPPY DIMMING	FLICKER	SHIMMER	AUDIBLE NOISE	DCES NOT TURN OFF ON	POPCORN	POPCORN	MIN/MAX LAMPS										
2	COOPER DAL06P-C2 (Universal)	600	1	Pass													1	10	✓					
3	LUTRON MA-PRO (Adaptive-Phase)	250/500	1	Pass														1	10			✓		
4	LUTRON RCL-153PNL (Forward-phase)	250	1	Pass														1	10			✓		
5	LEVITON 6672 (Forward-phase)	150/600	1	Pass														1	10			✓		
6	LUTRON AYCL-153P (Forward-Phase) Toggle Type	150	1	Pass														1	10			✓		
7	LUTRON LECL-153PH (Fprward-Phase) Luneva (C.L)	150	1	Pass														1	10			✓		
8	LEGRAND ADTP703TU (Adom Tru Universal)	450	1	Caution														1	30	F				
9	LEVITON IPE04-1L (ELV)	450	1	Caution														1	30	F				
10	LEVITON 6674, IPL06, DSL06, TSL06,(Univeral- Forwa	150	1	Pass														1	15	✓				
11	LEVITON RNL06-10Z	150/600	1	Pass														1	10			✓		
12	LUTRON RRD-PRO (Reverse-Phase)	250	1	Pass														1	10				✓	
13	LEVITON DSM10, TSM10 Forward-Phase (MLV, LED, C	450/1000	1	Pass														1	15	✓				
14	LUTRON DVCL-153P (Forward-Phase) Diva (C.L)	150	1	Pass														1	10			✓		
15	LUTRON MACL-153M (Forward-Phase) Maesteo (C.L)	150	1	Pass														1	10			✓		
16	LUTRON NTCL-250 NovaT (Forward-Phase)	250	1	Pass														1	10			✓		
17	StarFish/Satco S11268 (Forward Phase)	150	1	Caution														1	15	✓				Minimum two lamps
18	LUTRON CTRP,DVRP-253P (Reverse-Phase)	250	1	Pass														1	10				✓	
18	LUTRON MSCL-OP153M Forward-Phase MA(C.L OCS	150	1	Pass														1	10			✓		
20	LEVITON DSE06-10Z (ELV)	150	1	Pass														1	15	✓				
21	LEVITON DDL06 (Universal - Forward-Phase)	300/600	1	Pass														1	15	✓				
22	SATCO 86/103 Z-Wave (Forward-Phase)	150	1	Pass														1	15	✓				
23	LUTRON RRD-6CL (RA C.L Forward-Phase)	150	1	Pass														1	15	✓				
24	Legrand RH703PTUTC (Universal, C.L, MLV, ELV)	700/450	1	Caution														1	30	F				
25	Legrand RHCL450PTC (Forward-Phase)	700/450	1	Pass														1	15	✓				
26	LUTRON CTRP,DVRP-253P (Reverse-Phase)	250	1	Pass														1	10				✓	
27	COOPER TAL06P-C2 (Forward-Phase Toggle C.L)	300/600	1	Fail														1	F	F				
29	LUTRON PD-6WCL Caseta (Forward-Phase)	150/600	1	Pass														1	10			✓		
30	LUTRON PD-10WX Caseta (Forward-Phase)	450/1000	1	Pass														1	10			✓		
31	LEVITON DSL06-1LZ (Forward-Phase)	300/600	1	Pass														1	10			✓		
32	LEVITON 66ELV (ELV)	300/600	1	Fail														1	40	F				
33	LUTRON NTRP-250 (Reverse-Phase)	250	1	Pass														1	10				✓	
34	LEVITON DDMX1 (MLV, LED, INC, HLGN)	450/1000	1	Pass														1	10			✓		
35	COOPER RF9640-ND (Universal, ELV, MLV, LED, INC)	300w/600	1	Pass														1	10			✓		
36	COOPER VSUL06D (Universal, ELV, MLV, LED, INC)	300w/600	1	Pass														1	15	✓				
37	COOPER SUF7 (Universal, ELV, INC, HLGN)	450/600/700	1	Pass														1	15	✓				
38	COOPER DUL06P-C2 (Universal, ELV, MLV, LED, Inc)	300w/600	1	Pass														1	10			✓		
39	LEVITON DW6HD, DH6HD, DG6HD, DZ6HD, DL6HD (Forward-Phase)	300w/600	1	Pass														1	15	✓				
40	COOPER SAL06P Universal (ELV, MLV, LED)	300w/600	1	Pass														1	15	✓				
41	Precision MR4 2400 PLS 2-CH Control Adaptive Phase	1200/1200																						
42	Overdrive ODMR0205 2-Channel control, 10-amps	600/600																						

Power Factor	0.775
Volt	123.4v
Watts	7.55W
Amps	0.079
Frequency	60Hz

Unlike incandescent bulbs, LED's have electronic components inside of them that can make noise when the bulbs are on, especially when dimmed. ENERGY STAR requires 25 dB or less be emitted per bulb/fixture at 12 inches. The noise may be caused by a variety of reasons, but a small amount of noise isn't anything to worry about. An Electronic Low Voltage dimmer like the Lutron DVRP-253P series will almost always silence noise from most LED products. (Neutral connection required)

PLEASE NOTE: Compatibility list is based upon testing conducted in a lab simulated environment. Actual results may vary