	Manual Primary To 10 To				02/11/2022			Pass		Product Model # \$21226, \$21227, \$21228, \$21229, \$21230, \$21231, \$21232, \$21233, \$21242, \$212-										√	
Visual Dimmer Testing Report Card			DATE TESTED ✓	02/11				Caution Fail		Product	3, S21244										
	/		' /			/_	7	7	7	7	7	7			_	s G25 Clear and White 90CRI				7	///
		_{ke} /		6	SERLINGS OF	RESTER VIEW	5/ ₅₄	ANE	ANT	MAG		/	/ 4	RH	Or ROLL		MG S		/	/	Judges Half Her Beddied
	MANUFACT	, node:	Sinne wet		SERIA!	PALIFE .	S JAL RANGE	SEASTRANE	SEATIRATE STE	South Fire	KEP IN	AME P. D.L.	BLE HOSE	Story of	OT ZO	OPEN J	MAZ-LAMPS	ring % God	85.		se High
ſ				1		N.S.	, XX	Š	<u> </u>	<u> </u>	/ s ^r	P ₂	8	* * O		1	10	/ 6°.	∕ 💖	/ **.	, Ho.
2	COOPER	DAL06P-C2 (Universal) MA-PRO (Adaptive-Phase)	600 250/500	1	Pass											1	10	•		1	
4	LUTRON	RCL-153PNL (Forward-phase)	250/300	1	Pass											1	10		1	•	
5	LEVITON	6672 (Forward-phase)	150/600	1	Pass											1	10		·		
6	LUTRON	AYCL-153P (Forward-Phase) Toggle Type	150	1	Pass											1	10		1		
7	LUTRON	LECL-153PH (Fprfward-Phase) Lunea (C.L)	150	1	Pass											1	10		1		
8	LEGRAND	ADTP703TU (Adorn Tru Universal)	450	1	Fail											3	F	F			
9	LEVITON	IPE04-1L (ELV)	450	1	Pass											1	10		*		
10	LEVITON	6674, IPL06, DSL06, TSL06,(Univeral- Forward	150	1	Pass											1	10		\		
11	LEVITON	RNL06-10Z	150/600	1	Pass											1	10	*			
12	LUTRON	RRD-PRO (Reverse-Phase)	250	1	Pass											1	10			1	
13	LEVITON	DSM10, TSM10 Forward-Phase (MLV, LED, CF	450/1000	1	Pass											1	10	\			
14	LUTRON	DVCL-153P (Forward-Phase) Diva (C.L)	150	1	Pass											1	10		\		
15	LUTRON	MACL-153M (Forward-Phase) Maesteo (C.L)	150	1	Pass											1	10		\		
16	LUTRON	NTCL-250 NovaT (Forward-Phase)	250	1	Pass											1	15		\		
17	StarFish/Satco	S11268 (Forward Phase)	150	1	Pass											1	10		✓		
18	LUTRON	CTRP-253P (Reverse-Phase)	250	1	Pass											1	10			1	
18	LUTRON	MSCL-OP153M Forward-Phase MA(C.L OCS)	150	1	Pass											1	10		✓		
20	LEVITON	DSE06-10Z (ELV)	150	1	Pass											1	10		✓		
22	SATCO	86/103 Z-Wave (Forward-Phase)	150	1	Caution											1	10	1			Quick Stobe at the Highest Dim Level
23	LUTRON	RRD-6CL (RA C.L Forward-Phase)	150	1	Pass											1	15		✓		
24	Legrand	RH703PTUTC (Universal, C.L, MLV, ELV)	700/450	1	Fail											2	20	F			Min 2-Lamps
25	Legrand	RHCL450PTC (Forward-Phase)	700/450	1	Pass											1	10		✓		
26	LUTRON	DVRP-253P (Reverse-Phase)	250	1	Pass											1	10			1	
27	COOPER	TAL06P-C2 (Forward-Phase Toggle C.L)	300/600	1	Pass											1	15	1			
29	LUTRON	PD-6WCL Caseta (Forward-Phase)	150/600	1	Pass											1	10		✓		
30	LUTRON	PD-10WX Caseta (Forward-Phase)	450/1000	1	Pass											1	10		✓		
31	LEVITON	DSL06-1LZ (Forward-Phase)	300/600	1	Pass											1	10		✓		
32	LEVITON	66ELV (ELV)	300/600	1	Pass											1	10				
33	LUTRON	NTRP-250 (Reverse-Phase)	250	1	Pass											1	10			1	
34	LEVITON	DDMX1 (MLV, LED, INC, HLGN)	450/1000	1	Pass											1	15		✓		
35	COOPER	RF9640-ND (Universal, ELV, MLV, LED,INC)	300w/600	1	Pass											1	15		✓		
36	COOPER	VSUL06D (Universal, ELV, MLV, LED, INC)	300w/600	1	Pass											1	15		✓		
37	COOPER	SUF7 (Universal, ELV, INC, HLGN)	450/600/700	1	Pass											1	20	✓			
38	COOPER	DUL06P-C2 (Universal, ELV, MLV, LED, Inc)	300w/600	1	Pass											1	20	✓			
39	LEVITON	DW6HD, DH6HD, DG6HD, DZ6HD, DL6HD (Forward- Phase)	300w/600	1	Pass											1	10		✓		
40	COOPER	SAL06P Universal (ELV, MLV, LED)	300w/600	1	Fail											1	F	F			
41 42	Precision Overdrive	MR4 2400 PLS 2-CH Control Adaptive Phase ODMR0205 2-Channel control, 10-amps	1200/1200 600/600																		
F	Power Factor Volt	0.766 123.0V																			
ļ	Watts	4.14w 0.043																			
į	Amps Frequence	0.043 60Hz	o noise when the hulbs																		